



## OEM-1

### Interfacing Information Bulletin **Number 3**

April 7, 1998

**Vehicles:** 1992 Chevrolet Lumina. Vehicles with one Delco/ Bose amplifier located in the trunk.

**Product:** ADD-GM21, OEM-1, AMP-RCA.

**Symptom:** When adding a aftermarket amplifier to the factory system the rear channels may not work or be at very low volume. Front channels work fine.

**Correction:** On the ADD-GM21 harness, connect the green/black wire and white/black wires together at the 18 pin Molex connector.

**Cause:** Some vehicles that have only one amplifier for the four speakers use one common audio return wire, instead of two. ( one for front and one rear) The ADD-GM21 harness is made for the more popular systems that use two audio return wires. Connecting the green/black and the white/black commons all four audio channels.