



# OEM-1

## Interfacing Information Bulletin Number 7

August 7, 1998

**Vehicles:** General Motors vehicles with Delco Bose system

**Product:** AMP-UNV

**Symptom:** When using the AMP-UNV cable with GM cars, care must be taken to insure that the audio return wires are properly terminated. Incorrect wiring may cause rear speaker output to be low and / or the left front speaker output to be low.

**Correction:** Connect the AMP-UNV cable as shown below for your system.

	AMP-UNV	GM-12	GM-21	GM-32
4 amp system	Connect WHT/BLK & GRY/BLK To: Connect GRN/BLK & PUR/BLK To:	Terminal D Terminal K	Terminal 3 Terminal 19	---
1 amp system	Connect WHT/BLK, GRY/BLK, GRN/BLK & PUR/BLK To:	---	Terminal 3	Terminal F14

Terminal D is in the white plug

Terminal K is in the blue plug

Terminal #3 is top row 3<sup>rd</sup> from right with locking tab up ( sometimes a white connector) looking into connector ( not wire side)

Terminal #19 is bottom row 2<sup>nd</sup> from left ( sometimes a blue connector)

Terminal F14, bottom row with locking tab up, 3<sup>rd</sup> from the right looking into connector ( not wire side)